



FortiManager - Release Notes

Version 5.6.5

FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO GUIDE

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET COOKBOOK

<http://cookbook.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/support-and-training/training.html>

NSE INSTITUTE

<https://training.fortinet.com>

FORTIGUARD CENTER

<https://fortiguard.com/>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdocs@fortinet.com



July 13, 2018

FortiManager 5.6.5 Release Notes

02-565-496996-20180713

TABLE OF CONTENTS

Change Log	5
Introduction	6
Supported models	6
Minimum screen resolution	6
Special Notices	7
FortiAP Manager per-device management option	7
Traffic Shaping Policies	7
WebSocket Implementation	7
Virtual Wire Pair Support after Upgrade to 5.6.2 or Later	7
FortiGate VM 16/32/UL license support	8
Hyper-V FortiManager-VM running on an AMD CPU	8
IPsec connection to FortiOS for logging	8
VM License (VM-10K-UG) Support	8
System Configuration or VM License is Lost after Upgrade	8
FortiOS 5.4.0 Support	9
Local in-policy after upgrade	9
ADOM for FortiGate 4.3 Devices	9
SSLv3 on FortiManager-VM64-AWS	9
Port 8443 reserved	9
Upgrade Information	10
Upgrading to FortiManager 5.6.5	10
Upgrading from 5.2.x	10
Downgrading to previous firmware versions	11
FortiManager VM firmware	11
Firmware image checksums	12
SNMP MIB files	12
Product Integration and Support	13
FortiManager 5.6.5 support	13
Feature support	16
Language support	17
Supported models	17
Compatibility with FortiOS Versions	25
Compatibility issues with FortiOS 5.6.3	25
Compatibility issues with FortiOS 5.6.0 and 5.6.1	25
Compatibility issues with FortiOS 5.4.9	25
Compatibility issues with FortiOS 5.4.8	25
Compatibility issues with FortiOS 5.2.10	26
Compatibility issues with FortiOS 5.2.7	26

Compatibility issues with FortiOS 5.2.6	26
Compatibility issues with FortiOS 5.2.1	26
Compatibility issues with FortiOS 5.2.0	27
Resolved Issues	28
AP Manager	28
Device Manager	28
Global ADOM	29
HA	29
Policy and Objects	30
Revision History	31
Script	31
System Settings	31
VPN Manager	31
Others	32
Common Vulnerabilities and Exposures	32
Known Issues	33
Device Manager	33
Script	33
Services	33
VPN Manager	33
Appendix A - FortiGuard Distribution Servers (FDS)	34
FortiGuard Center update support	34

Change Log

Date	Change Description
2018-06-28	Initial release of 5.6.5.
2018-07-03	Added FortiGate 6000 Series support to <i>Product Integration & Support > Supported Models > FortiGate Models > 5.4.</i>
2018-07-06	Added 464795 to <i>Resolved Issues > Common Vulnerabilities and Exposures.</i>
2018-07-13	Added 452732 to <i>Resolved Issues > Others.</i>

Introduction

This document provides the following information for FortiManager 5.6.5 build 1707:

- [Supported models](#)
- [Special Notices](#)
- [Upgrade Information](#)
- [Product Integration and Support](#)
- [Compatibility with FortiOS Versions](#)
- [Resolved Issues](#)
- [Known Issues](#)
- [FortiGuard Distribution Servers \(FDS\)](#)

For more information on upgrading your device, see the FortiManager *Upgrade Guide*.

Supported models

FortiManager version 5.6.5 supports the following models:

FortiManager	FMG-200D, FMG-200F, FMG-300D, FMG-300E, FMG-400E, FMG-1000D, FMG-2000E, FMG-3000F, FMG-3900E, FMG-4000D, and FMG-4000E.
FortiManager VM	FMG-VM64, FMG-VM64-AWS, FMG-VM64-Azure, FMG-VM64-HV (including Hyper-V 2016), FMG-VM64-KVM, and FMG-VM64-XEN (for both Citrix and Open Source Xen).

Minimum screen resolution

The recommended minimum screen resolution is 1280 x 800. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

Special Notices

This section highlights some of the operational changes that administrators should be aware of in 5.6.5.

FortiAP Manager per-device management option

FortiAP Manager now supports a new per-device AP management option. When this option is enabled, the WiFi settings are managed at each FortiGate device level. The Central WiFi settings of the ADOM are not applied to the per-device managed APs.

Traffic Shaping Policies

Starting from FortiManager 5.6.0, configuration for traffic shaping policies has been moved from individual FortiGate devices (the device database) to the ADOM database Policy Package. For FortiManager units that are upgraded from a previous release, a one-time operation of Importing all traffic shaping policies into the ADOM must be performed (a one-time manual or scripted reconfiguration can also be performed). Otherwise, the FortiManager will delete (purge) all existing traffic shaping policies on the FortiGate when installing the original policy package.

WebSocket Implementation

As of version 5.6.0, WebSocket protocol has been implemented to allow for more efficient communication between the FortiManager and the browser. WebSocket protocol uses the standard TCP 80/443 browser ports, and is transparent to the operator. If your browser is using a proxy to access the FortiManager, ensure there are no limitations or restrictions on the using WebSocket.

Virtual Wire Pair Support after Upgrade to 5.6.2 or Later

FortiManager 5.6.2 or later supports Virtual Wire Pair policies. After you upgrade FortiManager, you should import all policies and objects again from FortiGate units that use Virtual Wire Pair policies. Otherwise, a subsequent install may delete all policies on FortiGate units that reference a Virtual Wire Pair.

FortiGate VM 16/32/UL license support

FortiOS 5.4.4 introduces new VM license types to support additional vCPUs. FortiManager 5.6.0 supports these new licenses with the prefixes of FGVM16, FGVM32, and FGVMUL.

Hyper-V FortiManager-VM running on an AMD CPU

A Hyper-V FMG-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

IPsec connection to FortiOS for logging

FortiManager 5.4.2 and later does not support an IPsec connection with FortiOS 5.0/5.2. However UDP or TCP + reliable are supported.

Instead of IPsec, you can use the FortiOS reliable logging feature to encrypt logs and send them to FortiManager. You can enable the reliable logging feature on FortiOS by using the `configure log fortianalyzer setting` command. You can also control the encryption method on FortiOS by using the `set enc-algorithm default/high/low/disable` command.

VM License (VM-10K-UG) Support

FortiManager 5.4.2 introduces a new VM license (VM-10K-UG) that supports 10,000 devices. It is recommended to upgrade to FortiManager 5.4.2 or later before applying the new license to avoid benign GUI issues.

System Configuration or VM License is Lost after Upgrade

When upgrading FortiManager from 5.4.0 or 5.4.1 to 5.4.x or 5.6.0, it is imperative to reboot the unit before installing the 5.4.x or 5.6.0 firmware image. Please see the *FortiManager Upgrade Guide* for details about upgrading. Otherwise, FortiManager may lose system configuration or VM license after upgrade. There are two options to recover the FortiManager unit:

1. Reconfigure the system configuration or add VM license via CLI with `execute add-vm-license <vm license>`.
2. Restore the 5.4.0 backup and upgrade to 5.4.2.

FortiOS 5.4.0 Support

With the enhancement in password encryption, FortiManager 5.4.2 and later no longer supports FortiOS 5.4.0. Please upgrade FortiGate to 5.4.2 or later.



The following ADOM versions are not affected: 5.0 and 5.2.

Local in-policy after upgrade

After upgrading to FortiManager 5.4.1 or later, you must import or reconfigure local in-policy entries. Otherwise, the subsequent install of policy packages to FortiGate will purge the local in-policy entries on FortiGate.

ADOM for FortiGate 4.3 Devices

FortiManager 5.4 and later no longer supports FortiGate 4.3 devices. FortiManager cannot manage the devices after the upgrade. To continue managing those devices, please upgrade all FortiGate 4.3 to a supported version, retrieve the latest configuration from the devices, and move the devices to an ADOM database with the corresponding version.

SSLv3 on FortiManager-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiManager-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
set ssl-protocol tlsv1
end
```

Port 8443 reserved

Port 8443 is reserved for `https-logging` from FortiClient EMS for Chromebooks.

Upgrade Information

Upgrading to FortiManager 5.6.5

You can upgrade FortiManager 5.4.0 or later directly to 5.6.5. If you are upgrading from versions earlier than 5.4.x, you should upgrade to the latest patch version of FortiManager 5.4 first.



When upgrading from FortiManager 5.4 or 5.6.0 to 5.6.1, it is required to run the following CLI for proper rendering of GUI pages:

```
diagnose cdb upgrade force-retry resync-dbcache
```



When upgrading from FMG 5.2, an *Import Policy Package* should be performed on all FortiGates using *Local-In-Policies*. As of FMG 5.4, these are handled in Policies & Objects.



During upgrade from 5.2.4 or earlier, invalid dynamic mappings and duplicate package settings are removed from the ADOM database. Please allow sufficient time for the upgrade to complete.



For details about upgrading your FortiManager device, see the *FortiManager Upgrade Guide*.

Upgrading from 5.2.x

Starting with FortiManager 5.4.0, you can create a maximum number of Global and ADOM objects for each object category, and the maximum is enforced. The maximum numbers are high and unlikely to be met. The purpose of the maximum is to help avoid excessive database sizes, which can impact performance.

During upgrade from FortiManager 5.2.x to 5.4.x to 5.6.5, objects are preserved, even if the 5.2 ADOM contains more than the maximum number of allowed objects. If you have met the maximum number of allowed objects, you cannot add additional objects after upgrading to FortiManager 5.6.5.

Following are examples of object limits:

- Firewall service custom: 8192 objects
- Firewall service group: 2000 objects

If you have reached the maximum number of allowed objects, you can reduce the number of objects by deleting duplicate or obsolete objects from the ADOM.

You can also reach the maximum number of allowed objects if you have multiple FortiGate/VDOMs in the same ADOM. You can reduce the number of objects by moving the FortiGates/VDOMs into different ADOMs.

Downgrading to previous firmware versions

FortiManager does not provide a full downgrade path. You can downgrade to a previous firmware release via the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrading process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format {disk | disk-ext4 | disk-ext3}
```

FortiManager VM firmware

Fortinet provides FortiManager VM firmware images for Amazon AWS, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiManager VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiManager VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `FMG_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.
- `.hyperv.zip`: Download the package for a new FortiManager VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Azure.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, FMG_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip.

- `.out`: Download the firmware image to upgrade your existing FortiManager VM installation.
- `.hyperv.zip`: Download the package for a new FortiManager VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

VMware ESX/ESXi

- `.out`: Download the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the FortiManager product data sheet available on the Fortinet web site, <http://www.fortinet.com/products/fortimanager/virtualappliances.html>. VM installation guides are available in the [Fortinet Document Library](#).

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in select *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiManager version 5.00 file folder.

Product Integration and Support

FortiManager 5.6.5 support

The following table lists 5.6.5 product integration and support information:

Web Browsers

- | |
|---|
| <ul style="list-style-type: none">• Microsoft Internet Explorer version 11 or Edge 40
Due to limitation on Microsoft Internet Explorer or Edge, it may not completely render a page with a large set of policies or objects.• Mozilla Firefox version 60• Google Chrome version 67 <p>Other web browsers may function correctly, but are not supported by Fortinet.</p> |
|---|

FortiOS/FortiOS Carrier

- 5.6.4 to 5.6.5
- 5.6.2 to 5.6.3
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.2, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.6.3 on page 25](#).
- 5.6.0 to 5.6.1
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.6.0 to 5.6.1, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.6.0 and 5.6.1 on page 25](#).
- 5.4.9
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.4.9, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.4.9 on page 25](#).
- 5.4.1 to 5.4.8
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.4.8, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.4.8 on page 25](#).
- 5.2.8 to 5.2.13
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.10, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.2.10 on page 26](#).
- 5.2.7
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.7, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.2.7 on page 26](#).
- 5.2.6
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.6, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.2.6 on page 26](#).
- 5.2.2 to 5.2.5
- 5.2.1
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.1, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.2.1 on page 26](#).
- 5.2.0
FortiManager 5.6.5 is fully tested as compatible with FortiOS/FortiOS Carrier 5.2.0, with some minor interoperability issues. For information, see [Compatibility issues with FortiOS 5.2.0 on page 27](#).

FortiAnalyzer

- 5.6.0 to 5.6.4
- 5.4.0 to 5.4.4
- 5.2.0 to 5.2.10
- 5.0.0 to 5.0.13

FortiCache	<ul style="list-style-type: none">• 4.2.7• 4.1.6• 4.0.0 to 4.0.4
FortiClient	<ul style="list-style-type: none">• 5.6.0 to 5.6.6• 5.4.0 and later• 5.2.0 and later
FortiMail	<ul style="list-style-type: none">• 5.4.5• 5.3.12• 5.2.10• 5.1.7• 5.0.10 <p>Limited support. For more information, see Feature support on page 16.</p>
FortiSandbox	<ul style="list-style-type: none">• 2.5.2• 2.4.1• 2.3.3• 2.2.2• 2.1.2• 1.4.0 and later• 1.3.0• 1.2.0 and 1.2.3
FortiSwitch	<ul style="list-style-type: none">• 5.2.5
FortiWeb	<ul style="list-style-type: none">• 5.9.1• 5.8.6• 5.7.2• 5.6.1• 5.5.6• 5.4.1• 5.3.9• 5.2.4• 5.1.4• 5.0.6
FortiDDoS	<ul style="list-style-type: none">• 4.5.0• 4.4.2• 4.3.2• 4.2.3• 4.1.12 <p>Limited support. For more information, see Feature support on page 16.</p>
FortiAuthenticator	<ul style="list-style-type: none">• 5.2.2

Virtualization

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Citrix XenServer 6.2
- Linux KVM Redhat 6.5
- Microsoft Azure
- Microsoft Hyper-V Server 2008 R2, 2012 & 2012 R2
- OpenSource XenServer 4.2.5
- VMware
 - ESX versions 4.0 and 4.1
 - ESXi versions 4.0, 4.1, 5.0, 5.1, 5.5, 6.0, and 6.5



To confirm that a device model or firmware version is supported by current firmware version running on FortiManager, run the following CLI command:

```
diagnose dvm supported-platforms list
```



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Feature support

The following table lists FortiManager feature support for managed platforms.

Platform	Management Features	FortiGuard Update Services	Reports	Logging
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiAnalyzer			✓	✓
FortiCache			✓	✓
FortiClient		✓	✓	✓
FortiDDoS			✓	✓
FortiMail		✓	✓	✓
FortiSandbox		✓	✓	✓
FortiSwitch ATCA	✓			
FortiWeb		✓	✓	✓
Syslog				✓

Language support

The following table lists FortiManager language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Spanish		✓

To change the FortiManager language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can import language translation files for these languages via the command line interface using one of the following commands:

```
execute sql-report import-lang <language name> <ftp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <sftp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <scp> <server IP address> <user name>
    <password> <file name>
execute sql-report import-lang <language name> <tftp> <server IP address> <file name>
```

For more information, see the *FortiManager CLI Reference*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch ATCA, FortiWeb, and FortiCache models and firmware versions that can be managed by a FortiManager or send logs to a FortiManager running version 5.6.5.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

FortiGate models

Model	Firmware Version
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E, FortiGate 5000 Series: FG-5001C, FG-5001D FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM FortiGate Rugged: FGR-30D, FGR-35D, FGR-60D, FGR-90D	5.6

Model	Firmware Version
FortiGate: FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG 3800D, FG-3810D, FG-3815D, FG-3960E, FG3980E, FG-2000E, FG-2500E FortiGate 5000 Series: FG-5001C, FG-5001D, FG-5001E, FG-5001E1 FortiGate 6000 Series: FG-6000F, FG-6300F, FG-6301F, FG-6500F, FG-6501F FortiGate 7000 Series: FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8 FortiGate DC: FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC FortiGate Hardware Low Encryption: FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list. FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	5.4

Model	Firmware Version
FortiGate: FG-20C, FG-20C-ADSL-A, FG-30D, FG-30D-POE, FG-40C, FG-60C, FG-60C-POE, FG-60C-SFP, FG-60D, FG-60D-3G4G-VZW, FG-60D-POE, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-90D, FG-90D-POE, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-110C, FG-111C, FG-140D, FG-140D-POE, FG-140D-POE-T1, FG-200B, FG-200B-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-300C, FG-300D, FG-310B, FG-311B, FG-400D, FG-500D, FG-600C, FG-600D, FG-620B, FG-621B, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1240B, FG-1500D, FG-1500DT, FG-3000D, FG-3016B, FG-3040B, FG-3100D, FG-3140B, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3810A, FG-3810D, FG-3815D, FG-3950B, FG-3951B FortiGate 5000 Series: FG-5001A, FG-5001A-SW, FG-5001A-LENC, FG-5001A-DW-LENC, FG-5001A-SW-LENC, FG-5001B, FG-5001C, FG-5001D, FG-5101C FortiGate DC: FG-80C-DC, FG-300C-DC, FG-310B-DC, FG-600C-DC, FG-620B-DC, FG-621B-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1240B-DC, FG-1500D-DC, FG-3000D-DC, FG-3040B-DC, FG-3100D-DC, FG-3140B-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3810A-DC, FG-3810D-DC, FG-3815D-DC, FG-3950B-DC, FG-3951B-DC FortiGate Low Encryption: FG-20C-LENC, FG-40C-LENC, FG-60C-LENC, FG-80C-LENC, FG-100D-LENC, FG-200B-LENC, FG-300C-LENC, FG-310B-LENC, FG-600C-LENC, FG-620B-LENC, FG-1000C-LENC, FG-1240B-LENC, FG-3040B-LENC, FG-3140B-LENC, FG-3810A-LENC, FG-3950B-LENC FortiWiFi: FWF-20C, FWF-20C-ADSL-A, FWF-30D, FWF-30D-POE, FWF-40C, FWF-60C, FWF-60CM, FWF-60CX-ADSL-A, FWF-60D, FWF-60D-3G4G-VZW, FWF-60D-POE, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate Rugged: FGR-60D, FGR-100C FortiGate VM: FG-VM, FG-VM64, FG-VM64-AWSONDEMAND, FG-VM-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-XEN FortiSwitch: FS-5203B, FCT-5902D	5.2

FortiCarrier Models

Model	Firmware Version
FortiCarrier: FCR-3000D, FCR-3100D, FCR-3200D, FCR-3700D, FCR-3700DX, FCR-3800D, FCR-3810D, FCR-3815D, FCR-5001C, FCR-5001D, FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3240C, FCR-3600C, FCR-3700D-DC, FCR-3810D-DC, FCR-5001C FortiCarrier DC: FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3240C-DC, FCR-3600C-DC, FCR-3700D-DC, FCR-3800D-DC, FCR-3810D-DC, FCR-3815D-DC FortiCarrier VM: FCR-VM, FCR-VM64, FCR-VM64-AWS, FCR-VM64-AWSONDEMAND, FCR-VM64-HV, FCR-VM64-KVM	5.4

Model	Firmware Version
FortiCarrier: FCR-3000D, FCR-3100D, FCR-3200D, FCR-3240C, FCR-3600C, FCR-3700D, FCR-3700DX, FCR-3810A, FCR-3810D, FCR-3815D, FCR-3950B, FCR-3951B, FCR-5001A, FCR-5001B, FCR-5001C, FCR-5001D, FCR-5101C, FCR5203B, FCR-5902D FortiCarrier DC: FCR-3000D-DC, FCR-3100D-DC, FCR-3200D-DC, FCR-3700D-DC, FCR-3810D-DC FortiCarrier Low Encryption: FCR-5001A-DW-LENC FortiCarrier VM: FCR-VM, FCR-VM64, FCR-VM64-HV, FCR-VM64-KVM, FCR-Vm64-XEN, FCR-VM64-AWSONDEMAND	5.2

FortiDDoS models

Model	Firmware Version
FortiDDoS: FI-200B, FI400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B, FI-3000B	4.2, 4.1, 4.0

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E.	5.6
FortiAnalyzer VM: FAZ-VM64, FAZ-VM64-AWS, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	
FortiAnalyzer: FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B.	5.4
FortiAnalyzer VM: FAZ-VM64, FMG-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	5.2
FortiAnalyzer: FAZ-100C, FAZ-200D, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B FortiAnalyzer VM: FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM-KVM, FAZ-VM-XEN	5.0

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B FortiMail Low Encryption: FE-3000C-LENC FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3.7
FortiMail: FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B FortiMail VM: FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2.8
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.1.6
FortiMail: FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B FortiMail VM: FE-VM64	5.0.10

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox VM: FSA-VM	2.4.0 2.3.2
FortiSandbox: FSA-1000D, FSA-3000D, FSA-3500D FortiSandbox VM: FSA-VM	2.2.0 2.1.0
FortiSandbox: FSA-1000D, FSA-3000D FortiSandbox VM: FSA-VM	2.0.0 1.4.2
FortiSandbox: FSA-1000D, FSA-3000D	1.4.0 and 1.4.1 1.3.0 1.2.0 and later

FortiSwitch ACTA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-5913C	5.2.0
FortiSwitch-ATCA: FS-5003A, FS-5003B FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.0.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3.0 4.2.0

FortiWeb models

Model	Firmware Version
FortiWeb: FWB-2000E	5.6.0
FortiWeb: FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E	5.5.3
FortiWeb VM: FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV, FWB-KVM, FWB-AZURE	
FortiWeb: FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.4.1
FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV	
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.3.8
FortiWeb VM: FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	
FortiWeb: FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E	5.2.4
FortiWeb VM: FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E	4.0
FortiCache VM: FCH-VM64	

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-2000E	1.0
FortiProxy VM: FPX-KVM, FPX-VM64	

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-3000B, FAC-3000D, FAC-3000E, FAC-VM	4.0 and 4.1

Compatibility with FortiOS Versions

This section highlights compatibility issues that administrators should be aware of in 5.6.5.

Compatibility issues with FortiOS 5.6.3

Bug ID	Description
469993	FortiManager has a different default value for switch-controller-dhcp-snooping from that on FortiGate.

Compatibility issues with FortiOS 5.6.0 and 5.6.1

Bug ID	Description
451036	FortiManager may return verification error on <code>proxy enable</code> when installing a policy package.
460639	FortiManager may return verification error on <code>wtp-profile</code> when creating a new VDOM.

Compatibility issues with FortiOS 5.4.9

Bug ID	Description
486592	FortiManager may report verification failure on the following attributes for RADIUS users: <code>rsso-endpoint-attribute</code> <code>rsso-endpoint-block-attribute</code> <code>sso-attribute</code>

Compatibility issues with FortiOS 5.4.8

Bug ID	Description
469700	FortiManager is missing three wtp-profiles: FAP221E, FAP222E, and FAP223E.

Compatibility issues with FortiOS 5.2.10

The following table lists interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS 5.2.10.

Bug ID	Description
397220	FortiOS 5.2.10 increased the maximum number of the firewall schedule objects for 1U and 2U+ appliances. As a result, a retrieve may fail if more than the maximum objects are configured.

Compatibility issues with FortiOS 5.2.7

The following table lists interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS 5.2.7.

Bug ID	Description
365757	Retrieve may fail on LDAP User Group if object filter has more than 511 characters.
365766	Retrieve may fail when there are more than 50 portals within a VDOM.
365782	Install may fail on system global optimize or system fips-cc entropy-token.

Compatibility issues with FortiOS 5.2.6

The following table lists interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS 5.2.6.

Bug ID	Description
308294	1) New default wtp-profile settings on FOS 5.2.6 cause verification errors during installation. 2) FortiManager only supports 10,000 firewall addresses while FortiOS 5.2.6 supports 20,000 firewall addresses.

Compatibility issues with FortiOS 5.2.1

The following table lists interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS version 5.2.1.

Bug ID	Description
262584	When creating a VDOM for the first time it fails.
263896	If it contains the certificate: <code>Fortinet_CA_SSLProxy</code> or <code>Fortinet_SSLProxy</code> , <code>retrieve</code> may not work as expected.

Compatibility issues with FortiOS 5.2.0

The following table lists known interoperability issues that have been identified with FortiManager version 5.6.5 and FortiOS version 5.2.0.

Bug ID	Description
262584	When creating a VDOM for the first time it fails.
263949	Installing a VIP with port forwarding and ICMP to a 5.2.0 FortiGate fails.

Bug ID	Description
230199	FortiManager allows the creation of a new FAP-320C WTP profile on a FortiOS 5.0.5 device causing the install to fail. FAP-320C is new for FortiOS 5.0.6.

Bug ID	Description
226064	Attempting to install time zones 79 and 80 fails. These time zones were added in FortiOS 5.0.5.
226078	When the password length is increased to 128 characters, the installation fails.
226098	When installing a new endpoint-control profile, installation verification fails due to default value changes in FortiOS 5.0.5.
226102	If DHCP server is disabled, installation fails due to syntax changes in FortiOS 5.0.5.
226203	Installation of address groups to some FortiGate models may fail due to table size changes. The address group table size was increased in FortiOS 5.0.5.
226236	The <code>set dedicated-management-cpu enable</code> and <code>set user-anonymize enable</code> CLI commands fail on device install. These commands were added in FortiOS 5.0.5.
230199	FortiManager allows the creation of a new FAP-320C WTP profile on a FortiOS 5.0.4 device causing the install to fail. FAP-320C is new for FortiOS 5.0.6.

Resolved Issues

The following issues have been fixed in 5.6.5. For inquiries about a particular bug, please contact [Customer Service & Support](#).

AP Manager

Bug ID	Description
462857	Following changes in an AP profile, FortiManager may install unrelated local user group and radius server to VDOM root.
465297	Users should be able to add more than one entry to the MAC Address Access Control List.
492723	AP Manager should be able to push override password settings.
494971	FortiAPs are not displayed in the AP Manager Map View after upgrade.
464811	Updated AP name may be reverted back to its default name if users do not install the change in a while.

Device Manager

Bug ID	Description
399893	FortiManager cannot show named address in Destination field of the router table.
408280	FortiManager may show FortiGate mobile token status as Unknown while it is pending.
434101	FortiManager is missing Endpoint Control replacement message in device configuration and system template.
459990	User should be able to resize the following windows: installation preview, view config revision, and database configuration view.
460403	FortiManager may not be able to generate an interface of type vxlan.
474241	The reserved management interface should be configurable as same subnet as another interface.
474245	Policy Install fails due to set disk-usage log command inconsistency.
481011	Individual VDOM should not be placed into backup mode ADOM when adom-mode is set to Advanced.
482033	FortiManager should be use the same GUI style for the Column Name as Source & Destination under Policy route.

Bug ID	Description
484600	FortiManager may not support enable/disable routes in Device Manager.
485722	Diffie-Hellman Groups 30, 29, 28, 27 and GCM encryption algorithms may be missing in IPSec Phase 2.
486515	Users may be unable to change upload-option for Fortianalyzer-2.
489545	VDOMs are not sorted in alphabetical order under Managed FortiGate tree view.
491102	Password expiration date is set for new administrators even though the feature is disabled.
491113	It is not possible to edit Replacement Messages via System's Replacement Message Group option.
207797	Device Manager System Information does not display correct FortiGate' system time.
462851	The <code>ha-direct</code> option should exist in SNMP v3 in provisioning template.
464267	When deleting a VDOM, FortiManager shows a pop up that disappears very quickly and it does not show details of VDOM references.
477142	Cloning a DHCP server may fail at the first attempt.
478338	First column of policy route list is incorrectly labeled as sequence number.
478444	Policy package status may not change to <i>Modified</i> in workflow mode.
487425	Policy Package status may incorrectly change when making changes to a package that has device groups as target.

Global ADOM

Bug ID	Description
482925	Internet Service destination is not displayed in IPv4 Header/Footer Policy in Global ADOM.
465511	Task Monitor does not give the exact status of total and pending tasks when an <code>automatic-install</code> is performed from the Global ADOM.

HA

Bug ID	Description
480462	FortiManager Slave may fail to synchronize when users add a lot of admin users to the Master.

Policy and Objects

Bug ID	Description
448895	There may be a performance issue with policy package check.
450509	Tokens should not be shown in the token list if they have been assigned to specific users.
463920	Address groups should highlight the addresses searched.
465620	Intrusion Prevention <code>log-attack-context</code> and <code>rate-mode</code> are not configurable on FortiManager.
471030	FortiManager allows users to use Wildcard entries under Web Rating Overrides.
474868	<code>Block intra-zone traffic</code> setting is not enabled by default in Zone.
478047	Add an option to disable dynamic mappings caused by different address comments.
481560	There is no validation check for FQDN addresses.
481873	A new firewall address object must not contain the default value: <code>0.0.0.0/0.0.0.0</code> .
485687	Central NAT policy package installation may not follow the same logic that used in regular policy packages.
488159	Multiple Policy Packages status changed to Modified after making change to one Policy Package.
489045	Installation failure when trying to configure an Explicit Web Proxy HTTPS service with the same port value than HTTP.
493484	FortiManager cannot support IPS signatures with unknown options.
493591	The FSSO polling server that is inherited from Global ADOM should not be edited at the assigned ADOM.
469685	When editing policy objects and switching to Full Screen mode, the OK button is missing and changes cannot be applied.
478601	When a user searches for unused objects and attempt to delete all searched objects, none of the objects are deleted.
481378	FortiManager should have the same visibility for YouTube Restrict compared to FortiGate.
487995	Users are unable to import CA certificate to ADOM.
494108	When adding or removing an interface from a zone, <code>block intra-zone traffic</code> should not be unset.
496612	FortiManager should allow the same real interface to be used in policy interface and zone at the same time.

Revision History

Bug ID	Description
478606	The preview of a VDOM may show commands from other VDOMs.
487117	FortiManager may try to install <code>ssl-hpkp-age</code> and <code>ssl-hsts-age</code> despite being disabled.
487833	Installation may fail for VIP policies with a zone as a source interface.

Script

Bug ID	Description
480982	Progress bar for installing script may not work if the admin user has None access to <code>import-policy-packages</code> .
482929	Users may be unable to add/edit script details using IE 11.

System Settings

Bug ID	Description
481018	DST change may be incorrect for Israel.
485392	Unclear error messages may be displayed after adding a FortiAnalyzer into Device Manager.
485675	TACACS authentication may not work when there are multiple servers defined.
492000	Users may not be able to upgrade ADOM from 5.4 to 5.6.
465511	Task Monitor does not give exact status of total and pending tasks when Automatic Install is performed from a Global ADOM.

VPN Manager

Bug ID	Description
487098	Random auto-generated PSK may be identical in two separate VPN Manager topologies.
493738	Following any change in VPN community settings, FortiManager is incorrectly hashing the PSK.
472726	Users may not be able to add/edit bookmarks in VPN manager when workflow mode is enabled.

Bug ID	Description
480991	Verification fails when using <code>assign-ip-from usrgrp</code> in Device Manager VPN.

Others

Bug ID	Description
480551	SNMPwalk may fail with <i>Error: OID not increasing:</i> <code>IP-MIB::ipAdEntAddr</code> .
494586	The <code>svc cdb reader daemon</code> consumes high CPU resources when viewing VPN Phase 2 configuration.
469405	The process <code>uma_upd</code> may crash often.
480080	Unsetting <code>adom-mode</code> in config system global does not make adom-mode normal.
482779	JSON API may return a HTTP 503 error when attempting to change a policy scope member while having no write access to the ADOM.
452732	B1578: [UDM] the <code>fds</code> and <code>fgd</code> schedule update and polling frequency does not work on backend.

Common Vulnerabilities and Exposures

Visit <https://fortiguard.com/psirt> for more information.

Bug ID	Description
464795	FortiManager 5.6.5 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">CVE-2017-17541

Known Issues

The following issues have been identified in 5.6.5. For inquiries about a particular bug or to report a bug, please contact [Customer Service & Support](#).

Device Manager

Bug ID	Description
456821	After a model device is linked to a real device, the VDOM is not displayed.

Script

Bug ID	Description
486445	Wildcard RADIUS user may fail to schedule TCL scripts.

Services

Bug ID	Description
478050	When a FortiGate HA cluster uses FortiManager as FDS server it may display duplicate entries in <i>FortiGuard > Package Management > Service Status</i> after a failover.

VPN Manager

Bug ID	Description
478536	When pushing configuration from FortiManager to FortiGate, the outdated VPN should be deleted before creating a new VPN to avoid the duplicate remote gateway error.

Appendix A - FortiGuard Distribution Servers (FDS)

In order for the FortiManager to request and retrieve updates from FDS, and for FortiManager to serve as a FDS, please configure the necessary settings on all devices between FortiManager and FDS, or between FortiManager and FortiGate devices based on the items listed below:

- FortiManager accesses FDS for antivirus and attack updates through TCP/SSL port 443.
- If there is a proxy server between FortiManager and FDS, FortiManager uses port 80 to communicate with the proxy server by default and connects to the proxy server using HTTP protocol.
- If FortiManager manages a FortiGate device located behind a proxy server, the proxy server permits TCP/SSL traffic to pass through via port 443.

FortiGuard Center update support

You can configure FortiManager as a local FDS to provide FortiGuard updates to other Fortinet devices and agents on your network. The following table lists which updates are available per platform/version:


Platform	Version	Antivirus	AntiSpam	Vulnerability Scan	Software
FortiClient (Windows)	<ul style="list-style-type: none">• 5.0.0 and later• 5.2.0 and later• 5.4.0 and later• 5.6.0 and later	✓		✓	
FortiClient (Windows)	<ul style="list-style-type: none">• 4.3.0 and later	✓			
FortiClient (Windows)	<ul style="list-style-type: none">• 4.2.0 and later	✓	✓		✓
FortiClient (Mac OS X)	<ul style="list-style-type: none">• 5.0.1 and later• 5.2.0 and later• 5.4.0 and later• 5.6.0 and later	✓		✓	
FortiMail	<ul style="list-style-type: none">• 4.2.0 and later• 4.3.0 and later• 5.0.0 and later• 5.1.0 and later• 5.2.0 and later	✓	✓		
FortiSandbox	<ul style="list-style-type: none">• 1.2.0, 1.2.3• 1.3.0• 1.4.0 and later	✓			

Platform	Version	Antivirus	AntiSpam	Vulnerability Scan	Software
FortiWeb	<ul style="list-style-type: none">• 5.0.6• 5.1.4• 5.2.0 and later• 5.3.0	✓			



To enable FortiGuard Center updates for FortiMail version 4.2 enter the following CLI command:

```
config fmupdate support-pre-fgt-43
set status enable
end
```



Copyright© 2018 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.